



SERVICE PARTS LIST

BULLETIN NO.
55-24-1625

SPECIFY CATALOG NO. AND SERIAL NO. WHEN ORDERING PARTS		REVISED BULLETIN	DATE
1-9/16" (40mm) SDS-Max Rotary Hammer			Mar. 2015
CATALOG NO.	5317-59	STARTING SERIAL NO.	C85A
		WIRING INSTRUCTION SEE PAGE 4	

EXAMPLE:
Component Parts (Small #) Are Included
When Ordering The Assembly (Large #).

FIG.	PART NO.	DESCRIPTION OF PART	NO. REQ.
20	43-62-5316	Side Handle Assembly	(1)
20a	42-68-5316	Clamping Band	(1)
20b	06-54-5316	M8 x 6.5mm Square Nut	(1)
20c	44-40-5316	Clamp Holder	(1)
20d	43-98-5316	Side Handle	(1)
21a	05-78-5316	M4 x 14mm Pan Hd. Taptite T-20 (1 of 3)	(1)
22	42-36-5316	Belly Shroud	(1)
23	31-40-5316	Gearcase Assembly	(1)
24	14-46-5311	Ball Bearing and Rotary Seal Assembly	(1)
24a	45-06-5320	Rotary Seal	(1)
24b	34-40-5320	O-Ring	(1)
24c	02-04-5317	Ball Bearing	(1)
24d	45-88-5313	Snap Ring	(1)




FIG.	PART NO.	DESCRIPTION OF PART	NO. REQ.
32	34-40-5308●	O-Ring	(2)
41	16-07-5318	Service Armature	(1)
42	-----	Magnet Ring	(1)
43	02-04-0530	Ball Bearing	(1)
44	23-16-5316	Motor Shroud	(1)
45	31-05-5316	Baffle	(1)
46a	06-82-0995	M4 x 16mm Pan Hd. Plastite T-20	(2)
46b	06-82-0995	M4 x 16mm Pan Hd. Plastite T-20	(2)
47	31-15-5316	Motor End Cover	(1)
48	06-95-5316	M6 x 50mm Pan Hd. Taptite T-30	(4)
49	-----●	Carbon Brush Assembly	(1)
50	-----●	Carbon Brush Assembly with Cut-Off	(1)
51	22-20-5316	Brush Holder Assembly	(2)
52	05-78-5313	M4 x 9mm Pan Hd. Plastite T-15	(2)
53	43-83-5317	Inductor Assembly	(1)
54	-----	Motor Housing	(1)
55	18-07-5318	Service Field	(1)
56	05-78-5314	M4.5 x 56mm ST T-30	(2)
57	23-66-5315	Trigger Switch	(1)
58	22-09-5318	PCB Assembly	(1)
59	22-56-5317	Close End Connector	(1)
60	22-64-5317	Power Cord with Strain Relief	(1)




FIG.	PART NO.	DESCRIPTION OF PART	NO. REQ.
61	31-17-5317	Cord Clamp	(1)
62	31-40-5317	Motor Housing and Handle Cover Assembly	(1)
63	-----	Handle Cover	(1)
64	05-78-5311	M5 x 18mm ST Pan Hd. Plastite T-20	(4)
65	42-55-5317	Carrying Case	(1)
66	22-18-6030●	Brush Service Kit (Set of 2)	(1)
67	44-76-0210	Strain Relief	(1)

• See page 2 for the exploded view and parts listing of the mechanical portion of the tool and service fixtures.


• See page 3 for lubrication instructions, torques chart, maintenance instructions and service kits.

• See Page 4 for wiring instructions.

MILWAUKEE ELECTRIC TOOL CORPORATION
13135 W. Lisbon Road, Brookfield, WI 53005
Drwg. 4

Lubrication Note: MILWAUKEE recommends that scheduled maintenance of this Rotary Hammer include lubrication replacement, and replacement of vital O-rings and gaskets at each carbon brush change. Doing so will prolong the life of the hammer by reducing wear to gears and mechanism parts. The carbon brushes and armature commutator in this MILWAUKEE Rotary Hammer are designed and matched for many hours of reliable performance.


Pack the rear of the piston with grease. There is to be no lubrication on the face of the part.



Place 2-3/16 oz. (62g) of grease in the bottom of the gearcase

Place 5/8 oz. (18g) of grease in the rear of the barrel before installing the striker

Coat teeth of clutch assembly with grease



Washer #19 is to be located here on barrel #17h

1. Place washer #19 onto backside of barrel.
2. Place 18 grams of 'Q2' grease inside barrel.
3. Coat o-ring groove on ram and o-ring with grease prior to installing o-ring on ram.

Coat the assembled ram and o-ring with grease as shown below.
4. When placing ram assembly into barrel, **slowly** apply pressure to ram assembly.
5. Push the ram assembly until rear face is just below small hole in the barrel. **DO NOT** wipe off any excess grease that oozes out of holes.




Fig. 1

LUBRICATION NOTES: Type 'Q2' Grease, No. 49-08-5355 (2.8oz, 80g tube)

Prior to reinstalling, clean gear assemblies with a clean, dry cloth. Lightly coat all individual parts highlighted here with grease. Apply a greater amount of grease to all internal and external gear teeth. Place 18 grams of grease in the rear of the barrel prior to inserting the ram. Place the remaining grease in the bottom of the gearcase.

Coat o-ring and o-ring groove prior to installing o-ring.
With o-ring installed, coat around entire side of ram

Coat the inside of the spindle driver prior to assembly

22-18-6030 BRUSH SERVICE KIT

THIS KIT CONTAINS:

- | | | |
|---|-------|---------------------------|
| 1 | ----- | Carbon Brush |
| 1 | ----- | Carbon Brush with Pop Off |


14-46-6010 MAINTENANCE SERVICE KIT

THIS KIT CONTAINS:

- | | | |
|---|------------|------------------------------|
| 1 | 45-12-5316 | Rubber Dust Shield |
| 1 | 34-60-5316 | Retaining Ring |
| 2 | 34-40-5316 | Spindle O-Ring |
| 2 | 34-60-5319 | O-Ring |
| 2 | 34-60-5321 | O-Ring |
| 1 | 45-06-5170 | Felt Seal |
| 1 | 45-06-5180 | Rotary Seal |
| 1 | 45-88-5323 | O-Ring |
| 2 | 45-06-5317 | Turcon Seal |
| 1 | 34-40-5321 | Back Press Ring |
| 2 | 34-40-5310 | O-Ring |
| 1 | 45-06-5316 | Rubber Gasket |
| 2 | 34-40-5308 | O-Ring |
| 1 | 22-18-6030 | Brush Service Kit (Set of 2) |
| 1 | 49-08-5355 | 'Q2' Grease (2.8oz/80g tube) |

FASTENER TORQUE SPECIFICATIONS (FT./LBS.)

FIG. NO.	WHERE USED	SEATING TORQUE	
		In/Lbs	Nm
21a	Belly Shroud - 1x	19-25	2.2-2.8
21b	Selector Bracket Clamp Plate - 2x	19-25	2.2-2.8
29a	Gearcase Cover (middle & front positions - 4x)	50-55	5.6-6.2
29b	Gearcase Cover (rear position - 2x)	35-40	4.0-4.6
46a	Motor End Cover - 2x	8-12	0.9-1.4
46b	Cord Clamp - 2x	10-16	1.2-1.8
48	Motor Housing - 4x	47-53	5.4-6.0
52	Brush Holder Assemblies - 2x	10-16	1.2-1.8
56	Field - 2x	16-21	1.8-2.4
64	Handle Cover - 4x	23-28	2.6-3.2
	Switch Screw - 2x	3.5-6	0.4-0.7



WIRING SPECIFICATIONS

Wire No.	Wire Color	Origin or Gauge	Length	Terminals, Connectors and 1 or 2 End Wire Preparation
1	Blue	22-64-5317	----	Component of cord set. Connect to position 2↓ on bottom of switch.
2	Brown	22-64-5317	----	Component of cord set. Connect to position 1↓ on bottom of switch.
3	Green	----	----	Component of cord set. Route to ground screw at the top of the gearcase cover.
4	White	18-07-5318	----	Component of field. Join with red PCBA wire #9 and secure with close end connector 'C1'.
5	Black	18-07-5318	----	Component of field. Connect to front brush holder assembly. See bottom detail.
6	Black	23-94-5317	----	Leadwire assembly. Connect one end to top front left terminal on switch. Connect other end to back brush holder assy.
7	Black	22-09-5318	----	Component of PCBA. Connect to top rear left terminal on switch.
8	White	22-09-5318	----	Component of PCBA. Connect to top front right terminal on switch.
9	Red	22-09-5318	----	Component of PCBA. Join with white field wire #4 and secure with close end connector 'C1'.
10	Black	22-09-5318	----	Component of PCBA. Joined to female connector with white wire #11. Connect to male connector and wires #12 & 13.
11	White	22-09-5318	----	Component of PCBA. Joined to female connector with white wire #10. Connect to male connector and wires #12 & 13.
12	White	43-83-5318	----	Component of inductor assy. Joined to male connector with red wire #13. Connect to female connector and wires #10 & 11.
13	Red	43-83-5318	----	Component of inductor assy. Joined to male connector with white wire #12. Connect to female connector and wires #10 & 11.