

# WIRING INSTRUCTIONS

TITLE

"D"-HANDLE TOOLS


MILWAUKEE ELECTRIC TOOL CORP.

13135 WEST LISBON RD. BROOKFIELD, WIS.

DATE  
Aug. '75

BULLETIN  
58-01-0179

\* ON SOME TOOLS FIELD WIRE  
NO. 4 IS BROWN & NO. 6 IS RED



Refer to electrical parts chart for terminal and connector part nos.  
and quantity required – see drawing for actual hook-up.

NOTE:

All leads must be held to  $\pm 1/8"$ .  
All field leads to be measured from  
and perpendicular to laminations.  
All lead lengths are before stripping.

## WIRING SPECIFICATIONS

Wire No.	Wire Color	Origin or Gauge	Length	Terminal				Connector			
				T1	T2	T3	T4	C1	C2	C3	C4
1	BLACK	CORD	3-7/8	X							
2	WHITE	CORD	3-7/8	X							
3	GREEN	CORD	4-1/2		X						
4	WHITE*	FIELD	2-1/4	X							
5	WHITE	18	7-3/4	XX							
6	WHITE*	FIELD	10-1/8	X							

## ELECTRICAL PARTS

### TERMINAL DESCRIPTION

Code	Part No.	Qty.
T1	22-44-0090	6
T2	23-74-0390	1

### CONNECTOR DESCRIPTION

Code	Part No.	Qty.

### SWITCH DESCRIPTION

Code	Part No.	Qty.
S1	23-66-0505	1